



# AH-00212

## Fire Alarm Control Panel

### LED Description

- FIRE : Indicates fire status
- Power : Indicates unit is in normal status
- Short C. : Indicates short-circuit
- Discon. : Indicates disconnection
- S.T. : Controls H1 & H2 for activation, light on means inactive
- Bell : Activates unit's sounder and external bell, light on means inactive
- Reset : Turns system back to initial status

### Specification

Model	<b>AH-00212</b>
Power	220V AC/50Hz *Others also available
Battery Capacity	24V DC 0.8Ah
Charging Voltage, Current	26V DC 100~400mA *With auto adjustment function
Exterior Resistance	Round-trip under 50Ω
# of heat detector connected	No limit *Except electronic-type
# of smoke detector connected	30/zone *Horing Lih manufactured
Max. Output Current	500mA
Digital Switch	500000 Cycles Min. reliability
End of Line Resistor	10kΩ *One per zone
Material	1.2mm steel plate
Color	Ivory white *Others also available
Dimensions	280mm (H) x 160mm (W) x 70mm (D)



AH-02124 Annunciator

Approvals: 